

Amendments to the Claims:

Re-write the claims as set forth below. This listing of claims will replace all prior versions and listings, of claims in the application:

Listing of Claims:

1. (currently amended) An adaptive supply voltage and body bias apparatus comprising:

a master controller ~~including~~ operating responsive to an operation state value;

a dynamic voltage supplier operably coupled to the master controller, the dynamic voltage supplier operative to receive a supply voltage indicator from the master controller;

an adaptive body biaseer operably coupled to the master controller, the adaptive body biaseer operative to receive a body bias indicator from the master controller; and

a plurality of computing devices, each of the computing devices having one of a plurality of threshold voltages, the plurality of computing devices operative to receive a supply voltage from the dynamic voltage supplier and a body bias voltage from the adaptive body biaseer.

2. (original) The adaptive supply voltage and body bias apparatus of claim 1 further comprising:

a frequency monitor operably coupleable to the plurality of computing devices, the frequency monitor operative to receive an output frequency indicator from at least one of the plurality of computing devices.

3. (original) The adaptive supply voltage and body bias apparatus of claim 2 wherein the frequency monitor generates a frequency offset value.

4. (original) The adaptive supply voltage and body bias apparatus of claim 3 wherein the frequency offset value is based on a comparison of the output frequency indicator and a reference frequency indicator.

5. (original) The adaptive supply voltage and body bias apparatus of claim 3 wherein the frequency offset value is provided to the master controller, the master controller generating a second supply voltage indicator and a second body bias indicator in response to the frequency offset value and the operation state value, the master controller operative to provide the second supply voltage indicator to the dynamic voltage supplier and operative to provide the second body bias indicator to the adaptive body bias circuit.

6. (original) The adaptive supply voltage and body bias apparatus of claim 5 further comprising:

the plurality of computing devices operative to receive a second supply voltage from the dynamic voltage supplier and a second bias voltage from the adaptive body biaser.

7. (original) The adaptive supply voltage and body bias apparatus of claim 1 wherein the master controller receives the operation state value from a processing device.

8. (original) The adaptive supply voltage and body bias apparatus of claim 1 wherein the plurality of computing devices are disposed on a processing element.

9. (original) The adaptive supply voltage and body bias apparatus of claim 1 wherein the supply voltage indicator and the body bias indicator are voltages.

10. (currently amended) A method for providing an adaptive supply voltage and body bias voltage, the method comprising:

generating a supply voltage indicator and a body bias indicator in response to an operation state value;

generating a supply voltage in response to the supply voltage indicator;

generating a body bias voltage in response to the body bias indicator; and

providing the supply voltage and the body bias voltage to a plurality of computing devices, each of the computing devices having one of a plurality of threshold voltages.

11. (currently amended) The method of claim 10 further comprising:

generating an output frequency indicator from at least one of the plurality of computing devices;

providing the output frequency indicator to a frequency monitor; and

generating a frequency offset value based on the output frequency indicator and a reference frequency.

12. (original) The method of claim 11 further comprising:

providing the frequency offset value to a master controller;

generating a second supply voltage indicator and a second body bias indicator in response to the frequency offset value and the operation state value; and

providing the second supply voltage indicator to a dynamic voltage supplier and the second body bias indicator to an adaptive body biaser.

13. (original) The method of claim 12 further comprising:

generating a second supply voltage;

generating a second body bias voltage; and

providing the second supply voltage and the second body bias voltage to the plurality of computing devices.

14. (original) The method of claim 10 further comprising:

receiving the operation state value from a processing device.

15. (original) The method of claim 10 wherein the plurality of computing devices are disposed on a processing element.

16. (currently amended) An adaptive supply voltage and body bias apparatus comprising:

a master controller operative to receive an operation state value, the master controller operative to generate a supply voltage indicator and a body bias indicator based on the operation state value;

a dynamic voltage supplier operably coupled to the master controller, the dynamic voltage supplier operative to receive the supply voltage indicator;

an adaptive body biaseer operably coupled to the master controller, the adaptive body biaseer operative to receive the body bias indicator;

a plurality of computing devices, each of the computing devices having one of a plurality of threshold voltages, the plurality of computing devices operative to receive a supply voltage from the dynamic voltage supplier and a bias voltage from the adaptive body biaseer;

a frequency monitor operably coupleable to the plurality of computing devices, the frequency monitor operative to receive an output frequency indicator from at least one of the plurality of computing devices.

17. (original) The adaptive supply voltage and body bias apparatus of claim 16 wherein the frequency monitor generates a frequency offset value based on a comparison of the output frequency indicator and a reference frequency indicator.

18. (original) The adaptive supply voltage and body bias apparatus of claim 17 wherein the frequency offset value is provided to the master controller, the master controller generating a second supply voltage indicator and a second body bias indicator in response to the frequency offset value and the operation state value, the master controller operative to provide the second supply voltage indicator to the dynamic voltage supplier and operative to provide the second body bias indicator to the adaptive body bias circuit.

19. (currently amended) The adaptive supply voltage and body bias apparatus of claim 18 further comprising:

the plurality of computing devices operative to receive a second supply voltage from the dynamic voltage supplier and a second body bias voltage from the adaptive body biaser.

20. (currently amended) A method for tuning a supply voltage and a body bias for a processing device, the method comprising:

for a first sub-section of the processing device:

- (a) generating a supply voltage indicator and a body bias indicator in response to an operation state value;
- (b) generating a supply voltage in response to the supply voltage indicator;
- (c) generating a body bias voltage in response to the body bias indicator;

- (d) providing the supply voltage and the body bias voltage to a plurality of computing devices, each of the computing devices having one of a plurality of threshold voltages;
- (e) generating an output frequency indicator with at least one of the plurality of computing devices;
- (f) generating a frequency offset value based on the output frequency indicator and a reference frequency indicator; and
- (e) updating the supply voltage and the body bias voltage in response to the frequency offset value and the operation state value.

21. (original) The method of claim 20 further comprising:

dividing the processing device into a plurality of sub-sections, wherein each sub-section includes the plurality of computing devices, each of the plurality of computing devices have one of a plurality of threshold voltages.

22. (original) The method of claim 21 further comprising:

repeating steps (a) through (e) for each of a plurality of sub-sections of the processing device.

23. (original) The method of claim 22 wherein the operating state value may be one of a plurality of values for each of the sub-sections.

24. (new) An adaptive supply voltage and body bias apparatus comprising:

a dynamic voltage supplier operative to receive a supply voltage indicator;

an adaptive body biaseer operative to receive a body bias indicator; and

a plurality of computing devices, each of the computing devices having one of a plurality of threshold voltages, each of the plurality of computing devices operative to receive a supply

voltage from the dynamic voltage supplier and a body bias voltage from the adaptive body biaser.